

ET-52300 SERIES





AC Line Filters EMI / RFI Common Mode Choke





- Prevents noise emission, such as electromagnetic interference (EMI) & radio frequency interference (RFI)
- Protects AC side from the effects of switching regulators
- Wide range of available inductances and current ratings



VERTICAL





(BOTTOM VIEW)



HORIZONTAL



(BOTTOM VIEW)



UNIT:mm

Vertical Part No.	Horizontal Part No.	Inductance (mH MIN)	DCR (Ω Max)	Rated current Iac (A)
ET - 52301	ET - 52321	10	8.0	0.1
ET - 52302	ET - 52322	8	6.0	0.2
ET - 52303	ET - 52323	5	3.0	0.3
ET - 52304	ET - 52324	2	1.0	0.5
ET - 52305	ET - 52325	1	0.6	0.7
ET - 52306	ET - 52326	0.5	0.3	1.0

1. Inductance tested at 10kHz, 0.1Vrms.
2. Rated voltage : 250VAC/VDC
3. Withstanding voltage: 2000VAC (one minute,between lines).
4. Insulation resistance: at 500VDC, more than 100M Ω (between lines).
5. Electrical specifications at 25°C.